

## Halogen (< 75 V) Einseitig





### Anwendungsgebiete

- Microscopy
- Laboratory & Analysis
- UV Curing
- Fiber Illumination
- Surgical & Dental Overhead


### Produkteigenschaften

- Precise filament alignment with patented quartz pinch technology
- OSRAM HLX lamps provide 10% higher luminous efficacy over standard halogen
- Instant on and nearly constant luminous flux over the life of the lamp
- Dimmable







HALOGEN NIEDERVOLT LAMPE PG 22




LOW-VOLTAGE HALOGEN LAMP 64250




LOW-VOLTAGE HALOGEN LAMP 62138




LOW-VOLTAGE HALOGEN LAMP 64611



LOW-VOLTAGE HALOGEN LAMP 64668




LOW-VOLTAGE HALOGEN LAMP 64640



---

LOW-VOLTAGE HALOGEN LAMP 64628



---

LOW-VOLTAGE HALOGEN LAMP 64643

Technische Daten

|                         | General Product Information |        | Elektrische Daten | Physical Attributes & Dimensions |
|-------------------------|-----------------------------|--------|-------------------|----------------------------------|
| Produkt-Bezeichnung     | ANSI-Code                   | LIF    | Nennspannung      | Sockel (Normbezeichnung)         |
| 64222 10 W 6 V          | -                           | -      | 6 V               | PG22                             |
| 64223 10 W 6 V          | -                           | M/43   | 6 V               | G4                               |
| 64225 10 W 6 V          | ESA/FHS                     | M/29   | 6 V               | G4                               |
| 64250 HLX               | ESB                         | M/33   | 6 V               | G4                               |
| 64251 HLX               | -                           | -      | 6 V               | PG22                             |
| 64265 HLX               | -                           | -      | 6 V               | G4                               |
| 64260 30 W 12 V         | -                           | M/185  | 12 V              | PG22                             |
| 64275 AX                | -                           | M/137  | 6 V               | G4                               |
| 64258 20 W 12 V         | -                           | -      | 12 V              | G4                               |
| 64602 50 W 12 V         | -                           | M/134  | 12 V              | G6.35                            |
| 64610 HLX               | BRL                         | A1/220 | 12 V              | G6.35                            |
| 64611 HLX               | -                           | -      | 12 V              | G6.35                            |
| 64668 XIR               | -                           | -      | 22.8 V            | G6.35                            |
| 64621 HLX               | -                           | -      | 12 V              | PG22                             |
| 64623 HLX               | EVA                         | M/28   | 12 V              | GY6.35                           |
| 64638 HLX               | -                           | -      | 24 V              | G6.35                            |
| 64625 HLX               | FCR                         | A1/215 | 12 V              | GY6.35                           |
| 64628 100 W 12 V        | FDT                         | A1/261 | 12 V              | GY9.5                            |
| 62138 HLX               | -                           | -      | 12 V              | G6.35                            |
| 64626 HLX <sup>1)</sup> | EHE                         | A1/45  | 12 V              | PG22                             |
| 64647 120 W 24 V        | -                           | -      | 22.8 V            | G6.35                            |
| 64650 50 W 22,8 V       | -                           | -      | 22.8 V            | G6.35                            |
| 64633 HLX               | BRJ                         | A1/234 | 15 V              | G6.35                            |
| 64640 HLX               | FCS                         | A1/216 | 24 V              | G6.35                            |
| 64292 XIR               | -                           | -      | 22.8 V            | G6.35                            |
| 64642 HLX               | FDV                         | M/184  | 24 V              | G6.35                            |
| 64641 HLX               | -                           | -      | 24 V              | G6.35                            |
| 64643 150 W 24 V        | FDS                         | A1/262 | 24 V              | GY9.5                            |
| 64654 HLX <sup>1)</sup> | -                           | -      | 24 V              | GY9.5                            |
| 64655 HLX               | EHJ                         | A1/223 | 24 V              | G6.35                            |
| 64656 HLX               | FNT                         | -      | 24 V              | G6.35                            |
| 64657 HLX               | EVC                         | M/33   | 24 V              | G6.35                            |
| 64663 HLX               | EVD                         | A1/239 | 36 V              | G6.35                            |
| 64664 HLX               | -                           | A1/270 | 36 V              | G6.35                            |
| 64665 HLX               | -                           | A1/166 | 36 V              | G6.35                            |

|                     | Lebensdauer        |
|---------------------|--------------------|
| Produkt-Bezeichnung | Average Rated Life |
| 64222 10 W 6 V      | 300 hr             |
| 64223 10 W 6 V      | 300 hr             |
| 64225 10 W 6 V      | 100 hr             |

## Familiendatenblatt

| Produkt-Bezeichnung     | Lebensdauer        |
|-------------------------|--------------------|
|                         | Average Rated Life |
| 64250 HLX               | 100 hr             |
| 64251 HLX               | 100 hr             |
| 64265 HLX               | 100 hr             |
| 64260 30 W 12 V         | 50 hr              |
| 64275 AX                | 25 hr              |
| 64258 20 W 12 V         | 2000 hr            |
| 64602 50 W 12 V         | 1100 hr            |
| 64610 HLX               | 50 hr              |
| 64611 HLX               | 100 hr             |
| 64668 XIR               | 350 hr             |
| 64621 HLX               | 2000 hr            |
| 64623 HLX               | 1500 hr            |
| 64638 HLX               | 300 hr             |
| 64625 HLX               | 50 hr              |
| 64628 100 W 12 V        | 50 hr              |
| 62138 HLX               | 50 hr              |
| 64626 HLX <sup>1)</sup> | 50 hr              |
| 64647 120 W 24 V        | 1000 hr            |
| 64650 50 W 22,8 V       | 1000 hr            |
| 64633 HLX               | 50 hr              |
| 64640 HLX               | 50 hr              |
| 64292 XIR               | 600 hr             |
| 64642 HLX               | 300 hr             |
| 64641 HLX               | 200 hr             |
| 64643 150 W 24 V        | 100 hr             |
| 64654 HLX <sup>1)</sup> | 300 hr             |
| 64655 HLX               | 50 hr              |
| 64656 HLX               | 75 hr              |
| 64657 HLX               | 300 hr             |
| 64663 HLX               | 50 hr              |
| 64664 HLX               | 150 hr             |
| 64665 HLX               | 300 hr             |

<sup>1)</sup> Auf Anfrage

## Familiendatenblatt

---

### Sicherheitshinweise

Halogenlampen dürfen zur Vermeidung von Personen- oder Sachschäden nur in geeigneten Leuchten betrieben werden, die so konstruiert sind (Schutzschilde, Gitter etc.), dass bei einem eventuellen Lampenplatzer keine Teile/Splitter nach außen dringen können und dass beim Betrieb keine Ultraviolettstrahlung nach außen abgestrahlt werden kann. Ferner ist darauf hinzuweisen, dass beim Betrieb der Lampen verstärkte Wärmeentwicklung auftreten kann. Nähere Hinweise hierzu erhalten Sie auf Anfrage.

---

### Anwendungshinweis

Für weitere Anwendungsinformationen beachten Sie bitte das Produktdatenblatt.

---

### Haftungsausschluss

Änderungen und Irrtümer vorbehalten. Vergewissern Sie sich, dass Sie immer den neuesten Stand verwenden.