

---

## FKJ 64747 CP/71 1000W 230V 20/CS 1/SKU



---

### Product features and benefits

- Robust construction for reliable, lasting performance
- Consistent color over the life of the lamps
- Instant on and nearly constant luminous flux over the life of the lamp
- Broad product portfolio supporting the stage and studio markets
- Dimmable to 0% with traditional amber shift

---

### Areas of application

- Stage and theatre
- Studio, TV and film
- Professional Photography
- Club & Disco

## Product datasheet

### Technical data

#### General product information

Product Number	54669
Product Name	FKJ 64747 CP/71 1000W 230V 20/CS 1/SKU
General Description	1000 watt, high voltage, single ended, G22, CP/71, tungsten halogen
LIF Code	CP/71
Product Remark	- s (Operating Position) = Vertical, base down

#### Electrical data

Nominal Wattage	1000 W
Nominal Voltage	230 V

#### Light technical data

Luminous Flux	26000 lm
Light Center Length - LCL (in)	2.477 in
Light Center Length - LCL (mm)	63.5 mm
Color Temperature	3200 K
Average Rated Life	200 h


#### Physical attributes

Bulb Shape	T7
Maximum Overall Length (in)	5.46 in
Maximum Overall Length (mm)	140 mm
Length l (in)	5.46 in
Length l (mm)	140 mm
Length l max. (in)	5.46 in
Length l max. (mm)	140 mm
Diameter d (in)	1.024 in
Diameter d (mm)	26.00 mm
Distance a (in)	2.477 in
Distance a (mm)	63.5 mm
Reflector Coating	26.00

#### Additional product data

Lampholder	G22
Operating Position	s90
Maximum Base Temperature (°C)	350 C

## Product datasheet



### Packaging Information

Product number	EAN/UPC	Packaging	Quantity	Outside dimensions l x w x h	Gross weight
54669	4008321468635	Folding box (SKU)	1	2.2 in x 2.2 in x 6.8 in	0.3 lb
54669	10046135546690	Shipping box (Case)	20	11.6 in x 9.4 in x 7.5 in	6.2 lb

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

### Disclaimer

OSRAM does not accept liability for errors, changes and omissions.