

HBO 1000W/NEL 1/CS 1/SKU



Product features and benefits

- High spectral intensity with peak irradiance at 365nm wavelength, making it ideal for microlithography
- Ceramic housings designed specifically for high temperature halogen and metal halide applications for optimal exposure and throughput
- Designed for long lasting performance
- Qualified with Nikon

Areas of application

- Semiconductor

Product datasheet

Technical data

General product information

Product Number	69176			
Product Name	HBO 1000W/NEL 1/CS 1/SKU			
Family Brand Name	НВО			
Application	Semiconductor			
Product Remark	 Cathode base with cable connection (M5) Lamps suitable for pulse operation between 700W and 1000W. Maximum permissible average power is 750W (also for constant power operation). Cathode Base with cooling fins. Anode sleeve base without thread. 			

Electrical data

Nominal Wattage	750 W
Nominal Voltage	47 V
Current (A)	16 A
Type of Current	DC

Light technical data

Radiant intensity in 350-450 nm range (mW/sr)	8300 mW/sr	
Radiant Power in 350-450 nm range (W)	82 W	
Light Center Length - LCL (mm)	84.5 mm	
Average Rated Life	2500 h	

Physical attributes

Base Anode	SFa15-5/16	
Base Cathode	SFaX14-5/21	
Maximum Overall Length (mm)	190 mm	
Length l1 (mm)	190 mm	
Length l1 max. (mm)	190 mm	
Diameter d (in)	1.102 in	
Diameter d (mm)	28.00 mm	
Distance a (mm)	84.5 mm	
Electrode Gap - cold (mm)	3 mm	

Additional product data

Operating Position	Vertical, anode down
Operating Position	vertical, anoue down

Product datasheet

Maximum Base Temperature (°C)	200 C	
Cooling	Convection	
Lamp Type	DOUBLE ENDED	

Packaging Information

Product number	EAN/UPC	Packaging	Quantity	Outside dimensions l x w x h	Gross weight
69176	4050300412603	Shipping box (Case)	1	13 in x 4.3 in x 4.5 in	1.7 lb

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Disclaimer

OSRAM does not accept liability for errors, changes and omissions.