

QBM D4i LI R

Qualified Bluetooth mesh D4i Module | Light management systems



Product family features

- With/without Daylight and Occupancy Sensor DEXAL Module
- Qualified Bluetooth mesh enabled by Silvair
- Control of DEXAL drivers or DALI drivers with additional DALI bus power supply
- Intended for installation into a standard ½" knockout
- Works with OSRAM Hubsense
- Works with OSRAM DEXAL

Product family benefits

- Design freedom due to compact size
- Easy to integrate in luminaire
- Minimize internal wiring in combination with DEXAL drivers
- Secured product communication granted by ioXT and PSA Certificates

Areas of application

- Open offices
- Individual offices
- Conference rooms
- Classrooms
- Storage and break areas
- Stairways
- Toilets

Technical data

Electrical data

Input voltage DC	12...22.5 V
Peak input current	30 mA
Average input current	10 mA
Radio frequency	2.4 GHz
Maximum TX power	+4 dBm
Wireless protocol	Qualified Bluetooth mesh enabled by Silvair
Wireless range	13 m line of sight
System wattage	0.30 W
Standby power	< 150 mW
Screw thread length	25 mm
Required DALI current (typical)	10 mA
Peak DALI current	30 mA
Maximum start-up time (DALI)	-

Dimensions & weight



Length	36.0 mm
Diameter	28.0 mm
Mounting hole diameter	22.2...23.2 mm
Product weight	18.20 g
Wire preparation length, input side	7...9 mm
Cable cross-section, input side	0.25...0.75 mm ²
Maximum allowed cable length	10
Screw thread length	25 mm

Temperatures & operating conditions

Ambient temperature range	-20...+50 °C
---------------------------	--------------

Product datasheet

Permitted rel. humidity during operation	0...90 %
Temperature range at storage	0...70 °C
Permitted relative humidity at storage	0...95 %
Maximum temperature at tc test point	60 °C

Lifespan

Lifespan	50000 h
----------	---------

Capabilities

Control output	D4i
Number of connected drivers	4
Dimmable	Yes
Type of sensor	Daylight / PIR
Operating range, light sensor	-
Maximum installation height	-
Compatibility	Works with OSRAM HubSense / Works with OSRAM DEXAL
Status Indicator	Green: network Status / Red: Motion detected
Reset	Magnetic ¹⁾
Number of control outputs	-
Dimming interface	D4i
Type of installation	Luminaire integration
Control interface	qualified Bluetooth mesh
Detection angle (Light sensor)	-
Detection angle (PIR)	-

¹⁾ by magnet

Certificates & standards

Approval marks – approval	CE / ioXT / PSA
Type of protection	IP54

Logistical data

Commodity code	90314990000
----------------	-------------

Environmental information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (RECh)	
Date of Declaration	16-08-2023
Primary Article Identifier	4052899627192
Candidate List Substance 1	Lead



Product datasheet

CAS No. of substance 1	7439-92-1
Safe Use Instruction	The identification of the Candidate List substance is sufficient to allow safe use of the article.
Declaration No. in SCIP database	9d5330f7-4d93-4e2f-ae30-cc72fa07cff1

Additional product information

- By integrating the device into a casing the wireless range could be affected, in particular by metal surfaces. Therefore, the wireless range needs to be verified after integration.
- The device could be reset to factory default by placing a strong Neodym magnet (e.g. N35, d=6.35 mm x h=1.59 mm) near the corner of the bezel for 5 seconds.
- The status LED of the device indicates following Network status. Fast blinking (Blue): Not connected to a network, Slow blinking (Blue); Connected to a network, Blink twice (Blue): Mesh package received, Long blink (Blue) Factory reset, Blink one (Red): Motion detected
- The device has passed successfully the SILVAIR Testing process.
- The device can be put into operation using the OSRAM HubSense Commissioning Tool (<https://platform.hubsense.eu>), subject to prior acceptance of the Terms of Use and the Privacy Policy.
- OSRAM may terminate or suspend the use of the HubSense Commissioning Tool at any time and for any or no reason in its sole discretion, even if access and use is continued to be allowed to others.
- The device complies with Bluetooth mesh Standard v1.0. It can also be used in 3rd party Bluetooth mesh network, that complies with this standard and that supports the mesh models of this device, and with certain 3rd party commissioning tools, that support the mesh models of this device. In order to ensure correct interoperability a verification with the 3rd party network components and the 3rd party commissioning tool is necessary in advance. Please contact OSRAM (support@hubsense.eu) to receive the actual list of supported models for this device.
- OSRAM shall have no liability for any 3rd party commissioning tool and does not make any representations, express or implied, about the availability and/or performance of such commissioning tool.
- OSRAM shall have no liability for and does not make any representations, express or implied, about the connectivity of OSRAM QBM products with any other products, that have passed the SILVAIR Testing process.

Download Data

File	
	Product Datasheet QBM D4i R DS 050821
	Brochures Technical application guide DEXAL LED drivers (EN)

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4052899627192	QBM D4i LI R	Shipping carton box 50	330 mm x 287 mm x 195 mm	18.47 dm ³	1530.00 g

Product datasheet

Logistical Data

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.