

Product datasheet P PAR 16 80 120° 6.9 W/827 GU10

PARATHOM PAR16 | LED reflector lamps PAR16 with retrofit pin base





June 11, 2023, 04:41:07 P PAR 16 80 120° 6.9 W/827 GU10

Technical data

Electrical data

Rated wattage	6.90 W
Nominal wattage	6.90 W
Nominal voltage	220240 V
Claimed equiv. conventional lamp power	80 W
Operating frequency	5060 Hz
Max. lamp no. on circuit break. 10 A (B)	59
Max. lamp no. on circuit break. 16 A (B)	97
Nominal current	0.051 A


Photometrical data

180 cd
575 lm
575 lm
2700 К
≥80
Warm White
≤6 sdcm
575 lm
575 lm
210 cd
2700 К
575 lm
0.70

Light technical data

Beam angle	120 °
Nominal beam angle	120 °
Rated beam angle (half peak value)	120.00 °
Starting time	< 0.5 s

Dimensions & weight



Overall length	55.0 mm
Diameter	51.0 mm
Outer bulb	PAR51
Product weight	48.00 g
Length	55.0 mm
Maximum diameter	51.0 mm

Temperatures & operating conditions

Lifespan

Nominal lamp life time	15000 h
Rated lamp life time	15000 h
Number of switching cycles	100000
Lumen maintenance at end of service life	0.70

Additional product data

Base (standard designation)	GU10
Mercury content	0.0 mg
Mercury-free	Yes
Appropriate disposal acc. to WEEE	Yes
Product remark	All technical parameters apply to the entire lamp/Due to the complex production process for light-emitting diodes, the typical values shown for the technical LED parameters are purely statistical values that do not necessarily match the actual technical parameters of each individual product, which can vary from the typical value

Capabilities

Dimmable	No

Certificates & standards

Energy efficiency class	A+
Energy consumption	7 kWh/1000h
Type of protection	IP20

Country specific categorizations

ILCOS	DRPAR-6,9/827-220-240-GU10-50/120
Order reference	LPPAR1680120 6,

Environmental information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)

Date of Declaration	18-04-2022
Primary Article Identifier	4058075815872
Declaration No. in SCIP database	In work

Ecodesign regulation information:

Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

References / Links

For further products and actual information concerning LED lamps see

www.osram.com/ledlamps

For Guarantee see https://

www.inventronics-light.com/multilevel-guarantees

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

OSRAM is distribution partner of LEDVANCE of LAMPS

OSRAM

OSRAM GmbH Marcel-Breuer-Strasse 6 80807 Munich, Germany