Product family datasheet

ORIGINAL MINIXEN

Original spare part

The cost-effective original spare parts

ORIGINAL MINIXEN signal lamps for cars can be used for interior lighting as well as reading lights. Discover these original spare parts from OSRAM with reliable OEM quality and a wide product range.

© 2026, OSRAM GmbH. All rights reserved.

Product family datasheet

Technical data

	Electrical Data					Photometric Data
Product description	**Power input**	**Nominal voltage**	**Nominal wattage**	**Power input tolerance**	**Test voltage**	**Nominal luminous flux**
ORIGINAL MINIXEN 2886X	6 W	12 V	6 W	±10 %	13.5 V	85 lm
ORIGINAL MINIXEN 3886X	6 W	12 V	6 W	±10 %	13.5 V	80 lm

	Physical Attributes & Dimensions			Lifetime Data
Product description	**Lamp base**	**Length**	**Diameter**	**Lifespan B3**
ORIGINAL MINIXEN 2886X	W2.1x9.5d	26.8 mm	10.0 mm	400 hr
ORIGINAL MINIXEN 3886X	BA9s	27.4 mm	9 mm	400 hr

		Certificates & standards	Environmental & Regulatory Information Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)		
Product description	**Lifespan Tc**	**ECE category**	**Primary article identifier**	**Candidate list substance 1**	**Declaration no. in SCIP database**
ORIGINAL MINIXEN 2886X	1000 hr	-	4050300888668 | 4052899560604 | 4008321094667	No declarable substances contained	No declarable substances contained
ORIGINAL MINIXEN 3886X	1000 hr	-	4050300885896 | 4008321095787	No declarable substances contained	No declarable substances contained

© 2026, OSRAM GmbH. All rights reserved.

Product family datasheet

Download Data

	File
	User instruction GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

© 2026, OSRAM GmbH. All rights reserved.