

6.6 Eine stromgesteuerte Halogenlampe mit Pk30d-Fassung für den Seriellen Betrieb

Anwendungsgebiete


- Flugfeldbeleuchtung



Produkteigenschaften

- Low maintenance costs due to long lamp life
- Reliable and consistent light output enhances visibility over the life of the lamp
- FAA approved in conjunction with many OEM fixtures
- Durable construction provides resistance to the effects of vibration
- Broad product portfolio for runway, taxiway, and approach lighting
- IR radiation provides guidance in low visibility conditions
- Flicker-free operation
- Ability to reduce light output when needed
- Mercury-free





Connector A, female

PK30d Connector A female

Technische Daten

	General Product Information	Elektrische Daten		Lebensdauer
Produkt-Bezeichnung	LIF	Nennleistung	Nennspannung	Average Rated Life
64319 Z/C 45-15	-	45 W	6.8 V	1500 hr
64317 C 45-15	J1/76	45 W	6.8 V	1500 hr
64317 IRC-C 45-30	J1/76	45 W	6.82 V	3000 hr
64318 A 45-15	J1/77	45 W	6.8 V	1500 hr
64328 HLX-A 65-15	-	65 W	9.8 V	1500 hr
64328 HLX-Z/C 65-15	-	65 W	9.8 V	1500 hr
64341 HLX-A 100-15	J1/79	100 W	15.2 V	1500 hr
64341 HLX-Z/C 100-15	J1/79	100 W	15.2 V	1500 hr
64342 HLX-C 100-15	J1/80	100 W	15.2 V	1500 hr
64361 HLX-A150-15	J1/83	150 W	22.7 V	1500 hr
64361 HLX-Z/C150-15	J1/83	150 W	22.7 V	1500 hr
64382 HLX-A 200-15	J1/84	200 W	30.3 V	1500 hr
64318 Z/C 45-15	J1/77	45 W	6.8 V	1500 hr
64319 A 45-15	-	45 W	6.8 V	1500 hr
64382 HLX-C 200-15	J1/84	200 W	30.3 V	1500 hr

Familiendatenblatt

Sicherheitshinweise

Halogenlampen dürfen zur Vermeidung von Personen- oder Sachschäden nur in geeigneten Leuchten betrieben werden, die so konstruiert sind (Schutzschild, Gitter etc.), dass bei einem eventuellen Lampenplatzer keine Teile/Splitter nach außen dringen können und dass beim Betrieb keine Ultraviolettstrahlung nach außen abgestrahlt werden kann. Ferner ist darauf hinzuweisen, dass beim Betrieb der Lampen verstärkte Wärmeentwicklung auftreten kann. Nähere Hinweise hierzu erhalten Sie auf Anfrage.

Anwendungshinweis

Für weitere Anwendungsinformationen beachten Sie bitte das Produktdatenblatt.

Haftungsausschluss

Änderungen und Irrtümer vorbehalten. Vergewissern Sie sich, dass Sie immer den neuesten Stand verwenden.