

EVD 64663 HLX 400W 36V 40/CS 1/SKU



Product features and benefits

- Precise filament alignment with patented quartz pinch technology
- OSRAM HLX lamps provide 10% higher luminous efficacy over standard halogen
- Instant on and nearly constant luminous flux over the life of the lamp
- Dimmable

Areas of application

- Microscopy
- Laboratory & Analysis
- UV curing
- Fiber Illumination
- Surgical & Dental Overhead
- Club & Disco

Technical data

General product information

Product Number	54259
Product Name	EVD 64663 HLX 400W 36V 40/CS 1/SKU
Family Brand Name	XENOPHOT (HLX)
Application	Projector, Microfilm, Studio
LIF Code	A1/239
Product Remark	– s (Operating Position) = Vertical, base down

Electrical data

Nominal Wattage	400 W
Nominal Voltage	36 V
Type of Current	AC

Light technical data

Luminous Flux	16200 lm
Light Center Length - LCL (in)	1.404 in
Light Center Length - LCL (mm)	36 mm
Color Temperature	3250 K
Color Rendering Index	100
Average Rated Life	50 h

Physical attributes

Base	G6.35
Bulb Shape	R111
Maximum Overall Length (in)	2.34 in
Maximum Overall Length (mm)	60 mm
Length l (in)	2.34 in
Length l (mm)	60 mm
Length l max. (in)	2.34 in
Length l max. (mm)	60 mm
Diameter d (in)	0.630 in
Diameter d (mm)	16.00 mm
Distance a (in)	1.404 in
Distance a (mm)	36 mm
Filament	C-Bar-6
Filament Dimensions Length (in)	0.1910 in
Filament Dimensions Length (mm)	10 mm

Product datasheet

Filament Dimensions Width (in)	0.362 in
Filament Dimensions Width (mm)	9.3 mm

Additional product data

Operating Position	s 90
Lamp Type	HLX

Packaging Information

Product number	EAN/UPC	Packaging	Quantity	Outside dimensions l x w x h	Gross weight
54259	4050300006741	Folding box (SKU)	1	1 in x 0.9 in x 2.8 in	
54259	4050300890937	Shipping box (Case)	40	5.7 in x 4.2 in x 4.8 in	0.9 lb

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Disclaimer

OSRAM does not accept liability for errors, changes and omissions.