

ORIGINAL - S8 WEDGE BASE -

Original spare part



The cost-effective original spare parts

ORIGINAL signal lamps with plastic bases offer reliable OEM quality. The original spare parts are available for different applications.

Product datasheet

Technical data

Product information

Application (Category and Product specific)	Auxiliary lamp
---	----------------


General Product Information

Global order reference	3157A
------------------------	-------

Electrical Data

Nominal voltage	12.8 V
Nominal wattage	27/7 W
Test voltage	13.5 V

Physical Attributes & Dimensions



Diameter	26.5 mm
Diameter	26.5 mm
Product weight	7.26 g
Length	53.3 mm
Lamp base	W2.5x16q

Lifetime Data

Lifespan B3	550 / 2300 hr
Lifespan Tc	1315 / 5500 hr ¹⁾

¹⁾ Filament 1 / Filament 2

Capabilities

Technology	AUX ¹⁾
------------	-------------------

¹⁾ Auxiliary signal lamp

Product datasheet

Certificates & standards

ECE category	-
--------------	---

Environmental & Regulatory Information


Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACH)	
Primary article identifier	4052899304291
Candidate list substance 1	No declarable substances contained
Declaration no. in SCIP database	No declarable substances contained

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4052899304291	S8 WEDGE BASE 3157A	Unpacked 1	53 mm x 26 mm x 26 mm	0.04 dm ³	7.00 g
4052899304314	S8 WEDGE BASE 3157A	Shipping carton box 50	181 mm x 154 mm x 90 mm	2.51 dm ³	524.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data

File
 User instruction GPRS_Safety symbols instructions

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM