### Product datasheet

# **OSRAM**

## ORIGINAL - PSX PSX26W

## OSRAM spare parts



#### OSRAM spare parts

Discover our ORIGINAL PSX lamps. The spare parts are signal lamp types for different applications. They provide a high and constant luminous flux.

### Product datasheet

#### Technical data

### **Product information**

Application (Category and Product specific)	Auxiliary lamp
---	----------------

#### **General Product Information**

Global order reference	6851
------------------------	------

#### **Electrical Data**

Power input	26 W
Nominal voltage	12.0 V
Nominal wattage	24 W
Test voltage	13.5 V

#### **Photometric Data**

Nominal luminous flux	500 lm
Luminous flux tolerance	+10 %

### **Physical Attributes & Dimensions**

Diameter	18.5 mm
Product weight	9.60 g
Length	46.7 mm
Lamp base	PG18.5d-3

### Lifetime Data

Lifespan B3	500 hr
Lifespan Tc	1000 hr

## Capabilities

	1)
Technology	AUX 1)

<sup>1)</sup> Auxiliary signal lamp

#### Certificates & standards

ECE category	PSX26W
--------------	--------

## **Environmental & Regulatory Information**

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)		
Date of declaration	26-06-2024	
Primary article identifier	4062172160100	

### Product datasheet

Candidate list substance 1	No declarable substances contained	
Declaration no. in SCIP database	In work	

#### Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172160124	ORIGINAL - PSX PSX26W		- x - x -	8.54 dm <sup>3</sup>	

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

#### **Application advice**

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

